



www.GE-InterlogixSecurity.com

NetworX NX-4 Control Panel

Overview

The NX-4 is a feature-rich, entry level security system. The NX-4 uses advanced technology for burglary, fire and environmental detection without the high cost of similar controls. The NX-4 is a flexible security system that is both easy to install and simple to use. With up to eight zones, the NX-4 is ideal for apartment, small residential and small commercial applications.

High Standards

The panel comes standard with four hardwire zone inputs. Four programmable outputs can be set up to activate external devices during an alarm or other system event. The Modular design allows for complete integration of multiple systems within one enclosure. Adding more zones or expanding capability is fast and easy.

Easy Expansion

Expand the NX-4 capabilities by adding one of a variety of optional expansion modules. Modular design allows NetworX modules to slide into the enclosure easily for quick installations.

The NX-320E Smart Power Supply and Bus Expander, the NX-508E Output Module and the NX-534E Two-Way Voice Module are just a few of the flexible options for the NX-4.

Expand the system even further with a phone interface/voice module for on-site and off-site system control using touchtone phones.

Effortless Programming

Conduct quick and easy on-site programming with alphanumeric keypads and a menu driven text interface. Off-site programming is also available with the DL-900 software for Windows.



Standard Features

- **Expandable to 8 fully programmable hardwire and/or wireless zones**
- **Maximum of 8 keypads with 1 partition**
- **Eight user codes**
- **185-event history log that provides date, time, event and user number**
- **Wireless technology with up to 8 supervised zones**
- **Hardwire expansion up to 8 zones. Supports SIA and contact ID communication formats**

NetworX NX-4

Control Panel

Available Keypad Styles



LED



Fixed Display With Removable Door



LED With Removable Door



LCD With Removable Door

Specifications

Power

- Operating – 16.5VAC 40VA
- Auxiliary w/40VA or 50VA transformer – 1 Amp
- Auxiliary w/NX-320E power supply – 3 Amps*

Loop Resistance

- Standard loop – 300 Ohms Maximum
- Built-in siren driver 2 Tone (Steady & Yelp)
- Alarm current available (if above driver is not used) – 2.5 Amps
- Loop response – 500ms

Physical and Environmental

- Operating temperature – 32 to 120 °F (0 to 49 °C)
- Operating LCD keypad dimensions – 6.4"W 4.0"H 1.1" D
- LED keypad dimensions – 6.4"W 5.3"H 1.0" D
- Keypad material – white / ABS
- Enclosure dimensions – 9.25"W 8.25"H 3.5" D
- Enclosure color – off white
- Shipping weight – 8 lbs

Miscellaneous

- Alarm current available (if above driver is not used) – 2.5 Amps
- Loop response – 500ms

*When using the NX-320E (w/50VA transformer) rated at 2 Amps and NX-8 (w/40VA or 50VA transformer) rated at 1 Amp, the combined available power is 3 Amps.

Ordering Information

NetworX Part Number	Main Product Offering
NX-4	4-zone control only. Keypad and transformer sold separately.
NX-4-KIT	4-zone control with NX-108E keypad and transformer.
NX-108E	8-zone LED keypad.
NX-1308E	8-zone LED keypad with removable door.
NX-1448E	48-zone fixed display keypad.
NX-148E	48-zone custom display LCD keypad with removable door.
NX-408E	8-zone wireless expander receivers.



GE Interlogix

www.GE-InterlogixSecurity.com

12345 SW Leveton Drive
Tualatin, OR 97062
Phone: 503-692-4052
USA & Canada: 800-547-2556
Technical Service: 800-727-2339
Faxback: 800-483-2495

2266 Second Street North
North Saint Paul MN 55109
Phone: 651-777-2690
USA & Canada: 800-777-5485
Technical Service: 800-777-2624