



[www.GE-InterlogixSecurity.com](http://www.GE-InterlogixSecurity.com)

## NetworX NX-6 Control Panel

### Overview

The NX-6 is a full-featured, mid-sized security system that uses advanced technology for burglary, fire and environmental detection. The NX-6 is a flexible security system that is easy to install and simple to use. With two partitions and up to sixteen zones, the NX-6 can handle most medium size residential and commercial security needs.

### High Standards

The panel comes standard with six hardwire zone inputs. Four programmable outputs can be set up to activate external devices during an alarm or other system event. The Modular design allows for complete integration of multiple systems within one enclosure. Adding more zones or expanding capability is fast and easy.

### Easy Expansion

Expand the NX-6 capabilities by adding up to three optional Expander Modules. Modular design allows NetworX modules to slide into the enclosure easily for quick installations.

The NX-320E Smart Power Supply and Bus Extender, the NX-508E Output Module and the NX-534E Two-Way Voice Module are just a few of the flexible options for the NX-6.

Expand the system even further with a phone interface/voice module for on-site and off-site system control using touchtone phones.

### Effortless Programming

Conduct quick and easy on-site programming with alphanumeric keypads and a menu driven text interface. Off-site programming is also available with the DL-900 software for Windows.



### Standard Features

- **Expandable to 12 hardwire /16 wireless zones**
- **Maximum of 8 keypads with up to 8 per partition**
- **Up to 2 true partitions with separate account codes, entry/exit delays, and feature selections for each partition**
- **Forty user codes**
- **185-event history log that provides date, time, event and user number**
- **Wireless technology with up to 16 supervised zones**
- **Hardwire expansion up to 16 zones.**
- **Supports SIA and contact ID communication formats**

# NetworX NX-6

Control Panel

## Available Keypad Styles



LED



Fixed Display With Removable Door



LED With Removable Door



LCD With Removable Door

## Specifications

### Power

- Operating – 16.5VAC 40VA
- Auxiliary w/40VA or 50VA transformer – 1 Amp
- Auxiliary w/NX-320E power supply – 3 Amps\*

### Loop Resistance

- For standard loop – 300 Ohms Maximum
- For 2-wire smokes – 30 Ohms Maximum

### Physical and Environmental

- Operating temperature – 32 to 120 °F (0 to 49 °C)
- LCD keypad dimensions – 6.4"W 4.0"H 1.1" D
- LED keypad dimensions – 6.4"W 5.3"H 1.0" D
- Keypad material – white / ABS
- Enclosure dimensions – 11.25"W 11.25"H 3.5" D
- Enclosure color – off white
- Shipping weight – 9 lbs

### Miscellaneous

- Alarm current available (if above driver is not used) 2.5 Amps
- Loop response – 500ms

\*When using the NX-320E (w/50VA transformer) rated at 2 Amps and NX-8 (w/40VA or 50VA transformer) rated at 1 Amp, the combined available power is 3 Amps.

## Ordering Information

NetworX Part Number	Main Product Offering
NX-6	8-zone control only. Keypad and transformer sold separately.
NX-6-KIT	8-zone control with NX-108E keypad and transformer.
NX-108E	8-zone LED keypad.
NX-1316E	16-zone LED keypad with removable door.
NX-1448E	48-zone fixed display keypad.
NX-148E	48-zone custom display LCD keypad with removable door.
NX-408E/416E	8, 16-zone wireless expander receivers.



**GE Interlogix**

www.GE-InterlogixSecurity.com

12345 SW Leveton Drive  
Tualatin, OR 97062  
Phone: 503-692-4052  
USA & Canada: 800-547-2556  
Technical Service: 800-727-2339  
Faxback: 800-483-2495

2266 Second Street North  
North Saint Paul MN 55109  
Phone: 651-777-2690  
USA & Canada: 800-777-5485  
Technical Service: 800-777-2624